



Power harness

Install GPS trackers faster and easier with Power harness.

Power harness is used to install FM-Eco4 light and FM-Eco4 light S series trackers. CANbus and tachograph data is not available using Power harness.

Power harness connects via fuse box for increased safety.

Power harness is available with ATO and MINI fuse types.

- Faster and easier installation
- Professional installation
- Minimize risk of faulty installations

		Eco4 light Fuse Tap ATO	Eco4 light Fuse Tap MINI												
Environmental specifications															
Temperature range	-30 to +75 °C														
Electrical specifications															
Voltage range	Up to 32 V DC														
Fuse type	ATO, 1 A		MINI, 1 A												
Physical properties															
Wire cross sectional area	0.5 mm ² (20 AWG)														
Cable length	1 m														
Pinout															
<p>12 pin connector</p>															
<table border="1"> <thead> <tr> <th>Pin no.</th> <th>Wire color</th> <th>Function</th> </tr> </thead> <tbody> <tr> <td>1</td> <td>Black</td> <td>Ground</td> </tr> <tr> <td>2</td> <td>Red</td> <td>Power supply</td> </tr> <tr> <td>9</td> <td>Yellow</td> <td>Ignition</td> </tr> </tbody> </table>				Pin no.	Wire color	Function	1	Black	Ground	2	Red	Power supply	9	Yellow	Ignition
Pin no.	Wire color	Function													
1	Black	Ground													
2	Red	Power supply													
9	Yellow	Ignition													
Compatibility															
FM-Tco4 HCV FM-Tco4 LCV FM-Pro4	No														
FM-Eco4 FM-Eco4 S	No														
FM-Eco4 light FM-Eco4 light S	Yes														
FM-Plug4	No														

Ordering information

Power harness Eco4 light Fuse Tap ATO	1 m power harness with ATO fuse tap
Power harness Eco4 light Fuse Tap MINI	1 m power harness with MINI fuse tap

Warnings



Waste equipment should not be disposed of with your other household waste. The product must be taken to separate collection points at the product's end-of life.

Document application

Given parameter values and various characteristics within this document apply only to the most recent product hardware version.

Legal information

All rights reserved. Reproduction, transfer, distribution or storage of parts or all of the contents in this document in any form without the prior written permission of Ruptela is prohibited. Other products and company names mentioned in this document are trademarks or trade names of their respective owners.

Contact information:

Ruptela
Perkunkiemio g. 6
LT-12130 Vilnius, Lithuania
Phone: +37052045188
Web: www.ruptela.com

Datasheet v1.1
2019-01-21
Copyright © 2019 Ruptela