



## Power harness

Power harness is used to install FM-Eco4 light and FM-Eco4 light S series trackers. CANbus and tachograph data is not available using Power harness.

12-wire fused harness has additional wires for connecting accessories.

- Faster and easier installation

	Eco4 light 1 m 3-Wire Fused	Eco4 light 1 m 12-Wire Fused
<b>Environmental specifications</b>		
Temperature range	-35 to +70 °C	
<b>Electrical specifications</b>		
Voltage range	Up to 32 V DC	
Fuse type	ATO, 1 A	
<b>Physical properties</b>		
Wire cross sectional area	0.5 mm <sup>2</sup> (20 AWG)	
Cable length	1 m	
<b>Compatibility</b>		
FM-Tco4 HCV FM-Tco4 LCV FM-Pro4	No	
FM-Eco4 FM-Eco4 S	No	
FM-Eco4 light FM-Eco4 light S	Yes	
FM-Plug4	No	

## Ordering information

**Power harness Eco4 light 1 m 3-Wire Fused**

1 m power harness with power supply, ground and ignition wires and fuse

**Power harness Eco4 light 1 m 12-Wire Fused**

1 m power harness with 12 wires and fuse

## Warnings



Waste equipment should not be disposed of with your other household waste. The product must be taken to separate collection points at the product's end-of life.

## Document application

Given parameter values and various characteristics within this document apply only to the most recent product hardware version.

## Legal information

All rights reserved. Reproduction, transfer, distribution or storage of parts or all of the contents in this document in any form without the prior written permission of Ruptela is prohibited. Other products and company names mentioned in this document are trademarks or trade names of their respective owners.

### Contact information:

Ruptela  
Perkunkiemio g. 6  
LT-12130 Vilnius, Lithuania  
Phone: +37052045188  
Web: [www.ruptela.com](http://www.ruptela.com)

Datasheet v1.0  
2018-12-06  
Copyright © 2018 Ruptela