



## Power harness

Power harness is used to install Pro/Tco series trackers.

12-wire and 14-wire harnesses have 1 m length wires for more flexible tracker and accessory installation.

- Faster and easier installation

	Pro/Tco 1 m 12-Wire Fused	Pro/Tco 1 m 14-Wire Accessory																																													
<b>Environmental specifications</b>																																															
Temperature range	-35 to +70 °C																																														
<b>Electrical specifications</b>																																															
Voltage range	Up to 32 V DC																																														
Fuse type	ATO, 1 A																																														
<b>Physical properties</b>																																															
Wire cross sectional area	0.5 mm <sup>2</sup> (20 AWG)																																														
Cable length	1 m																																														
<b>Pinout</b>																																															
<div style="display: flex; justify-content: space-around;"> <div style="text-align: center;"> <p><b>12 pin connector</b></p> </div> <div style="text-align: center;"> <p><b>14 pin connector</b></p> </div> </div>																																															
<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>Pin no.</th> <th>Wire color</th> <th>Function</th> </tr> </thead> <tbody> <tr><td>1</td><td>Red</td><td>Power supply</td></tr> <tr><td>2</td><td>Black</td><td>Ground</td></tr> <tr><td>3</td><td>Pink</td><td>DIN1</td></tr> <tr><td>4</td><td>Grey</td><td>AIN1</td></tr> <tr><td>5</td><td>Blue</td><td>DIN2</td></tr> <tr><td>6</td><td>Green</td><td>AIN2</td></tr> <tr><td>7</td><td>White</td><td>DIN3</td></tr> <tr><td>8</td><td>Purple</td><td>DOUT1</td></tr> <tr><td>9</td><td>Yellow</td><td>Ignition/DIN4</td></tr> <tr><td>10</td><td>Orange</td><td>DOUT2</td></tr> <tr><td>11</td><td>Blue/Red</td><td>CAN Low</td></tr> <tr><td>12</td><td>White/Red</td><td>CAN High</td></tr> </tbody> </table>			Pin no.	Wire color	Function	1	Red	Power supply	2	Black	Ground	3	Pink	DIN1	4	Grey	AIN1	5	Blue	DIN2	6	Green	AIN2	7	White	DIN3	8	Purple	DOUT1	9	Yellow	Ignition/DIN4	10	Orange	DOUT2	11	Blue/Red	CAN Low	12	White/Red	CAN High						
Pin no.	Wire color	Function																																													
1	Red	Power supply																																													
2	Black	Ground																																													
3	Pink	DIN1																																													
4	Grey	AIN1																																													
5	Blue	DIN2																																													
6	Green	AIN2																																													
7	White	DIN3																																													
8	Purple	DOUT1																																													
9	Yellow	Ignition/DIN4																																													
10	Orange	DOUT2																																													
11	Blue/Red	CAN Low																																													
12	White/Red	CAN High																																													
<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>Pin no.</th> <th>Wire color</th> <th>Function</th> </tr> </thead> <tbody> <tr><td>1</td><td>Yellow</td><td>PortB-232 RX</td></tr> <tr><td>2</td><td>Black</td><td>Ground</td></tr> <tr><td>3</td><td>Orange</td><td>PortB-232 TX</td></tr> <tr><td>4</td><td>Red</td><td>1-Wire power</td></tr> <tr><td>5</td><td>Purple</td><td>PortA-232 RX</td></tr> <tr><td>6</td><td>Green/Yellow</td><td>1-Wire data</td></tr> <tr><td>7</td><td>Pink</td><td>PortA-232 TX</td></tr> <tr><td>8</td><td>White</td><td>CAN High</td></tr> <tr><td>9</td><td>Green</td><td>L-Line</td></tr> <tr><td>10</td><td>Blue</td><td>CAN Low</td></tr> <tr><td>11</td><td>Brown</td><td>K-Line</td></tr> <tr><td>12</td><td>Black</td><td>Ground</td></tr> <tr><td>13</td><td>White/Red</td><td>RS-485 A</td></tr> <tr><td>14</td><td>Yellow/Brown</td><td>RS-485 B</td></tr> </tbody> </table>			Pin no.	Wire color	Function	1	Yellow	PortB-232 RX	2	Black	Ground	3	Orange	PortB-232 TX	4	Red	1-Wire power	5	Purple	PortA-232 RX	6	Green/Yellow	1-Wire data	7	Pink	PortA-232 TX	8	White	CAN High	9	Green	L-Line	10	Blue	CAN Low	11	Brown	K-Line	12	Black	Ground	13	White/Red	RS-485 A	14	Yellow/Brown	RS-485 B
Pin no.	Wire color	Function																																													
1	Yellow	PortB-232 RX																																													
2	Black	Ground																																													
3	Orange	PortB-232 TX																																													
4	Red	1-Wire power																																													
5	Purple	PortA-232 RX																																													
6	Green/Yellow	1-Wire data																																													
7	Pink	PortA-232 TX																																													
8	White	CAN High																																													
9	Green	L-Line																																													
10	Blue	CAN Low																																													
11	Brown	K-Line																																													
12	Black	Ground																																													
13	White/Red	RS-485 A																																													
14	Yellow/Brown	RS-485 B																																													

	Pro/Tco 1 m 12-Wire Fused	Pro/Tco 1 m 14-Wire Accessory
<b>Compatibility</b>		
FM-Tco4 HCV FM-Tco4 LCV FM-Pro4	Yes	
FM-Eco4 FM-Eco4 S	No	
FM-Eco4 light FM-Eco4 light S	No	
FM-Plug4	No	

## Ordering information

<b>Power harness Pro/Tco 1 m 12-Wire Fused</b>	1 m power harness for Pro/Tco trackers with fuse
<b>Power harness Pro/Tco 1 m 14-Wire Accessory</b>	1 m accessory harness for Pro/Tco trackers

## Warnings



Waste equipment should not be disposed of with your other household waste. The product must be taken to separate collection points at the product's end-of life.

## Document application

Given parameter values and various characteristics within this document apply only to the most recent product hardware version.

## Legal information

All rights reserved. Reproduction, transfer, distribution or storage of parts or all of the contents in this document in any form without the prior written permission of Ruptela is prohibited. Other products and company names mentioned in this document are trademarks or trade names of their respective owners.

### Contact information:

Ruptela  
Perkunkiemio g. 6  
LT-12130 Vilnius, Lithuania  
Phone: +37052045188  
Web: [www.ruptela.com](http://www.ruptela.com)

Datasheet v1.1  
2019-01-21  
Copyright © 2019 Ruptela